

**AUTOMATIC NUMBER IDENTIFICATION
OUTPULSER CIRCUIT
OPERATION TESTS
STEP-BY-STEP OFFICES
ARRANGED FOR ANI-TYPE B**

1. GENERAL

1.001 This addendum replaces Addendum 1 of Section 227-545-500, Issue 3.

1.002 This addendum is reissued to correct verifications in Step 9 of Test E.

4. METHOD

The following changes apply to Part 4 of the section:

- (a) Test A, Steps 12c—revised
- (b) Test D, Steps 14d, 16d—revised
- (c) Test E, Steps 7c, 9—revised

STEP	ACTION	VERIFICATION
-------------	---------------	---------------------

A. Regular Call

12c If tip party has been simulated—
Restore TP key.

D. Work Timer

14d Operate OFF- and THO- keys associated with PBX groups arranged for AIOD service to select AIOD office code number.

Note: Any THO- key may be associated with an AIOD translator for number to be identified. Operate THO- key in accordance with local assignment for translator selection.

16d At trouble ticketer frame—
Momentarily operate AR key.

Minor alarm retired.

Check trouble ticket for:

- 5 in character position 3
- 9 in character position 8
- 3 in character position 25
- 7 in character position 27
- in character position 29
- 1 in character position 33.

Note: If trouble ticket was not printed, wait until trouble ticketer is idle; then restore ST key and repeat Steps 15d and 16d.

STEP	ACTION	VERIFICATION
------	--------	--------------

E. Timer Two—Continuity Check Failure

7c	If tip party has been simulated— Restore TP key.	
----	---	--

9	Operate ST key.	At OITT— OB, TRS, TM1, TM2, CCKF, RL lamps lighted. Trouble ticket printed. Minor alarm occurred. If ZM or no option is provided— IRL, I0, I2 lamps lighted.
---	-----------------	---