

SECONDARY CONSTANTS OF NONLOADED CABLE
26 GAUGE BST

at 68° F. *

Freq. kHz	Characteristic Impedance			
	R Ohms	X Ohms (neg.)	Z Ohms	Angle Degrees (neg.)
.1	2106	2098	2973	44.9
.2	1491	1484	2103	44.9
.3	1218	1211	1718	44.8
.5	945	937	1331	44.7
1	671	660	942	44.5
2	478	464	666	44.1
3	394	376	544	43.7
5	310	287	422	42.9
8	250	222	335	41.6
10	227	196	300	40.8
15	192	155	247	38.8
20	172	130	216	36.9

Through Carrier Frequencies – at 55° F. *

Freq. kHz	Characteristic Impedance			
	R Ohms	X Ohms (neg.)	Z Ohms	Angle Degrees (neg.)
.1	2081	2073	2937	44.9
.2	1473	1466	2078	44.9
.5	934	926	1315	44.7
1	664	652	931	44.5
2	473	458	659	44.1
5	306	283	417	42.8
10	225	193	297	40.7
15	191	152	244	38.6
20	171	127	213	36.7
50	131	67	147	27.1
100	118	39	124	18.1
200	112	22	114	11.4
250	110	19	112	9.9
500	106	13	107	6.7
1000	103	8	104	4.7
2000	101	6	101	3.2
4000	99	4	99	2.1
5000	98	3	98	1.8
10000	97	2	97	1.3

* For temperature variations see page 3.

at 68° F. *

Freq. kHz	Propagation Constant per mile			Phase Delay Sec./Mile (x 10 ⁻⁶)	Velocity of Propagation Miles/Sec. (x 10 ³)
	Attenuation		Phase Shift β radians		
	α nepers	dB			
.1	.105	.91	.105	166.48	6.0
.2	.148	1.28	.148	117.77	8.5
.3	.181	1.57	.181	96.24	10.4
.5	.233	2.03	.234	74.61	13.4
1	.329	2.85	.333	52.92	18.9
2	.461	4.01	.473	37.65	26.6
3	.561	4.87	.683	30.94	32.3
5	.714	6.20	.763	24.29	41.2
8	.885	7.68	.985	19.60	51.0
10	.976	8.47	1.117	17.77	56.3
15	1.155	10.03	1.415	15.02	66.6
20	1.291	11.22	1.691	13.45	74.3

Through Carrier Frequencies – at 55° F. *

Freq. kHz	Propagation Constant per mile			Phase Delay Sec./Mile (x 10 ⁻⁶)	Velocity of Propagation Miles/Sec. (x 10 ³)
	Attenuation		Phase Shift β radians		
	α nepers	dB			
.1	.103	.89	.103	163.77	6.1
.2	.145	1.26	.146	115.86	8.6
.5	.229	1.99	.231	73.37	13.6
1	.323	2.81	.327	52.03	19.2
2	.453	3.94	.465	37.02	27.0
5	.702	6.09	.751	23.91	41.8
10	.958	8.32	1.100	17.51	57.1
15	1.134	9.85	1.396	14.81	67.5
20	1.266	11.0	1.669	13.28	75.3
50	1.680	14.6	3.198	10.18	98.2
100	1.968	17.1	5.756	9.16	109.2
200	2.373	20.6	10.90	8.68	115.3
250	2.587	22.5	13.45	8.56	116.8
500	3.564	31.0	25.94	8.26	121.1
1000	5.162	44.8	50.39	8.02	124.7
2000	7.540	65.5	98.42	7.83	127.7
4000	10.95	95.1	193.1	7.68	130.1
5000	12.47	108.3	240.1	7.64	130.8
10000	18.73	162.7	472.7	7.52	132.9

Notes: dB = 8.686 α phase delay = $\beta/2\pi f$ velocity of propagation = $2\pi f/\beta$

* For temperature variations see page 3.

Estimated Average Temperature Variation *

Freq. kHz	per mile per degree F.			
	dB	Phase Radians	R Ohms	X Ohms
.3	.0020	.00023	1.083	-1.119
.5	.0026	.00030	.838	-.864
1	.0036	.00042	.595	-.619
2	.0051	.00059	.410	-.438
3	.0063	.00072	.331	-.364
5	.0081	.00092	.255	-.291
10	.0119	.00126	.175	-.208
15	.0149	.00151	.135	-.177
20	.0173	.00169	.109	-.155
50	.0265	.00228	.040	-.072
100	.0335	.00265	.007	-.070
200	.0373	**	**	**
250	.0380			
500	.0427			
1000	.0533			
2000	.0846			
4000	.1650			
5000	.2060			
10000	.4390			

* Average values between 34° and 76° F.

** At high frequency, inductance has a significant effect on phase shift and impedance; therefore, due to the uncertainty of the effect of temperature variation on inductance, the phase and impedance variations above 100 kHz are not given.