

HANDSET CORDS

1. GENERAL

- 1.01 This section includes information on cords used with KS-, F-, and G-type hand sets.
- 1.02 This section is reissued to add information on G3P, G3R, G3S, and G3T hand sets obtainable with 4' 6" cords.
- 1.03 Tables A, B, and C show the cords, their lengths, and a description of use.
- 1.04 For information on color, refer to the general section on station cords.

TABLE A
KS-16504 TYPE HAND SETS

Handset	Cord	Length	Used with
KS-16504, L1	H5U	4'	8A Announcement System
KS-16504, L2	H5W		9A Announcement System
KS-16504, L3	H5U		KS-19134, L1 Conference Set

TABLE B
F-TYPE HAND SETS

Handset*	Cord		Used with
	Black	Length	
	Vinyl Jacket†		
F1A	H3AS	4', 9', 13'	Telephone sets, 200, 300, and 400 types
F1B	H3AE	3'	Coin collectors, 181, 182, 183, 191, 195, 196, and 197 types
F1BR	H3AL‡ H3AT		
F1C	H3AD	1' 3"	Outdoor telephone sets, 300, 325, and 326 types
F1E	H3N		Elevator telephone set, 322 type
F1G	H3AS	4', 9', 13'	Telephone sets, 300 and 400 types
	H3AF‡	4', 9'	
F1GR	H3AR	4', 9', 13'	
F1H	H3AC‡	4'	Test sets, 85A, 86A, 87A and B, and 88A
F1K	H3AU	3'	Coin collector stations equipped with armored handset cord
F1L	H3AU		Coin collector stations equipped with stainless steel armored handset cord
F2A	H4CA	4'	PBX systems equipped with 289B plug
F2B	H4BU		Telephone sets, 307, 309, and 357 types
F2C			Private toll-line stations associated with 102-type key equipment
F2D	H4CE	8'	L carrier order wires
F2ER	H4CN	3'	(Conversion of nonhandset type coin collectors to handset type)
F2F	H4CB	4'	Order wires of TD-2 microwave system equipped with 289B plug
F2G	H4CE		
F3B	H4BY	4', 9', 13'	Telegraph position of toll-test board equipped with 289B plug
F3F			Key equipment, 102-type equipped with 289B plug
F3H	H4BW		4-wire private line equipment associated with 102A or 109A key equipment
F3J	H3AS		Key equipment, 102A
F3K F3L F3M	H4BW		Push-to-talk handsets
F3N	H4BY	4-wire private line equipment associated with 102A or 109A key equipment equipped with 289B plug	
F3P	H5R	4'	Key equipment, 102A
F3AAW	H5E§	5'	Test set, 83A for mobile radio telephone
F3ABW	H6A§		Test equipment for RCA and Motorola mobile telephone
F3ADW	H5T		4' 3"
	H5L‡		
F3AEW	H5H‡	3' 6"	General Electric mobile telephone systems equipped with 91-MC4M connector
F3WWR	H5T	5'	Mobile telephone primarily used with the 41A control unit
F5A	H4BC	3'	(Replaces F2E hand set when better transmission is required)
F6AR	H3AN‡	4'	Telephone set, 320 type
F6BR	H4CF		Telephone set, KS-14548 type and some KS-14476 explosion-proof sets
F6CR	H3AN‡		(Replaces F6A hand set when better transmission is required)

* The suffix R in the code number of a handset indicates that it is equipped with spring cord.

† With exceptions noted.

‡ Neoprene jacketed cord.

§ Textile covered cord.

TABLE C
G-TYPE HAND SETS

Handset*	Cord		Used with
	Vinyl Jacket†	Length	
G1AR§	H4CJ	4', 9', 13'	Telephone sets, 500 and 501 types
G1BR	H4BN‡ H4CP	3'	Coin collector, 200 type
G1DR	H4BL	7'	PBX system and order turrets equipped with 289B plug
G1FR	H4BN‡	3'	Telephone set, 570 type
G1J-3	H4CS	1' 2"	Telephone set, 525A and 525B
G3AR	H4CJ	4', 9', 13'	The PRINCESS set, 701 and 711 types
G3BR			Key equipment, 112A for SAGE
G3CR	H4CU	4', 9'	Key equipment, 700 type and telephone set, 610 type
G3DR	H4BL		Key equipment, 112A for SAGE
G3FR	H4CP	3'	Coin collector, 200 type (concentrator equipment)
G3L	H4CU	4', 9'	Key mounting, 400 type
G3MR	H4CW	3'	Coin telephone set, 2A1
G3R	H4DA	2' 5", 4' 6"	Coin collector stations equipped with stainless steel armored cord
G3P	H4CY		Coin telephone set, 1A1
G3S	H4CY		Coin telephone set, 1A type
G3T	H4DA		Coin telephone set, 223 and 224 types
G4AR	H4CJ		4', 9', 13'
G5AR	H5G‡	4'	Control unit, 47A-3 for MB- and MC-type mobile radio telephones
G5BR	H6C	4', 9', 13'	4-wire circuit systems of N. Y. Thruway and loudspeaker paging systems
G5CR	H4CM-3	7'	CAA and private line systems
G5ER	H5P	4'	Telephone set, 535 type
G5FR	H4BM		Bendix MRT9 radio pack set equipped with Amphenol 91-MC4M connector
G5GR	H4CJ	4', 9', 13'	2- or 4-wire private line stations and telephone set, 606 type
G5HR	H5P	4'	Key equipment, 102A
G5JR	H6D		Switching system, 300 type equipped with 338A plug
G5KR	H6E	4', 9', 13'	FARM INTERPHONE, 2A
G5LR	H6D	4'	Telephone set, 617 type
G5MR	H4CU		Command Post Alerting Networks (COPAN)
G6AR§	H4CJ		(Provides receiver amplification for customers with impaired hearing)
G7AR§			(Provides transmitter amplification for customers with inadequate speech volume)
G8A§			Telephone sets, 500, 600, and 700 types in noisy locations

* The suffix R in the code number of a handset indicates that it is equipped with a spring cord.

† With exceptions noted.

‡ Neoprene jacketed cord.

§ Make cord replacement for these handsets by modifying the H4CJ hand set cord as covered in section on connection and maintenance of handset.