

## TEST SET AND MISCELLANEOUS CORDS FOR STATION USE IDENTIFICATION


### 1. GENERAL

- 1.01** This section contains information on cords, their lengths, and description of uses. The cords are used with receivers, switches and dials, head telephone sets, test equipment, and associated station apparatus.
- 1.02** This section is being reissued to show cords D3AH, D3BP, D8P, D9H, D20G, D50H, D50P, D120J, L4BT, M2CB, M2CC, R2CC, R2CD, R2CJ, R2DA, R2DP, R2EE, R2FM, T7A, and W2BM manufacture discontinued (MD). Revision arrows have been used to denote the tables containing MD cords.
- 1.03** For information on colors, refer to the general section covering station cords.

♦TABLE A♦

RECEIVER AND TEST SET CORDS

CORD	LENGTH	USED WITH
R2BC	4'	Receiver, 716-type, cable splicer testing equipment
R2CC (MD)	4'3"	Test set, 19-type (MD), two 716-type receivers in series
R2CD (MD)	2'4"	Test sets 17D (MD), 17E (MD) and 19-type (MD), 716-type receiver
R2CJ (MD)	4'	Receiver, 717-type connected to a D-type handset mounting as an auxiliary receiver
R2DA (MD)	3'6"	Test set, J64044A, transmission measuring
R2DB	3', 6', 10'	Headset 1005, or a 2A amplifier detector
R2DE	4'	Test set, 2B (MD) noise measuring
R2DM	6'	Headset, chief operator to a 29A connecting block
R2DN	2'6"	Test sets, 54A and B
R2DP (MD)	8'	Dial Tandem Call Announcer System, two receivers in series
R2DW	3'	Receiver, 706-type (MD)
R2DY	3'	Receiver, 706-type (MD) coin collectors
R2EE (MD)	4'3"	Receiver, 716-type, two in series
R2FA	2', 4'	Receiver, 716-type or 723A
R2FL	4'3"	Receiver, 731A
R2FM (MD)	3', 6'	Receivers, radio, single sideband, types of LC, LD, LE, and the LE transmitter



### NOTICE

Not for use or disclosure outside the  
Bell System except under written agreement

♦TABLE B♦

## SWITCH AND DIAL MOUNTING CORDS

CORD	LENGTH	USED WITH
D3AH (MD)	3/8"*	Hand telephone sets, 211, 212, 213 (MD) and 214 (MD) types
D5W	2-3/4"†	Dial mounting, 6000F
D5AH	1-1/4"‡	Dial mounting, 6000D, 6044A (MD), and 6044B
D5AJ	1-1/4"‡	Dial mounting, 6044C-3
D5AM	11"	Coin collectors, 181 (MD), 183, (MD), 191, 193 (MD), 195, 196, 197, 198 (MD), 210 (MD), 212, 223, 230 (MD), 233 (MD), and 234 (MD) types
D6AE	1-1/4"§	Dial mounting, 6044D-3
D10P	5'6"	Dials, 1025A3 (MD), 1025W3 (MD)
D10R		
D14M	1'5"	Dials, 1035B3 (MD), 1035A3A (MD), 1035C3A, 1036D (MD), and 1036E

\* Free conductor lengths are 2 to 4 inches.

† Free conductor lengths are 7/8 to 2-5/8 inches.

‡ Free conductor lengths are 1-1/8 to 1-7/8 inches.

§ Free conductor lengths are 1 to 2 inches.

♦TABLE C♦

## TEST EQUIPMENT CORDS

CORD	LENGTH	USED WITH
2W37A	4'	These cords couple with the H2A cord associated with the 1011G (MD) handset
2W38A	5'	
2W39A	4'	
2W40A	4'	
2W41A	4'	
3W8A	5'	
H2A	10"	Handset, 1011G (MD)
H2B	4'	Handset, 1013A
P5M	5'6"	Multislot coin collectors not equipped to use P10B or P11C cords
P10B	6'	Coin collector, 236 (MD) and 1234 (MD) types
P11C	6'	Coin telephone sets 1A (MD), 2A (MD), 1C, 2C, and 1E.
W2AK	4'	Dial hand test set, D-81760
W2BA	4'	Test set, D-81761
W2BM (MD)	1'6"	Battery gauges, 35 and KS-8089
W2BT	4'	Handset, 1011B (MD)
W2ET	3'9"	Test set, KS-16990L1
W2EY	4'	Loop checker, 24A
W3AM	22'	Test set, 105A (MD) and 105B (MD)
W50A	7"	Key, 6050 series and telephone sets equipped with multiples of 25-pair cable.

♦TABLE D♦

## HEAD TELEPHONE SET CORDS

CORD	LENGTH	HEAD TELEPHONE SET
L2Y	4'6"	52E
L3K	5'	53N
L4BR	5'	53J
L4BS	5'	53JR
L4BT (MD)	5'	53K
L4BU	12'	53LR
L4BW	9', 15'	53MR, 53PR
L4BY	10'	52L
L4CA	7', 15'	52N
L4CB	7', 10'	52PR
L4CC	5', 7'	52M, 52S
L4CD	18'	52T
L4CH	5'2"	61A
L4CJ	5'2"	60A, 60C
L4CK	3'	61B
L4CL	3'	60B
L4CM	13'	60B, 61B
L6H	7'	52RR

♦TABLE E♦

## ASSOCIATED STATION APPARATUS CORDS

CORD	LENGTH	USED WITH
D2M	18'	50A Conference Set
D3BP (MD)	5'6"	Lamp indicator, 15, 17 types, 21B (MD), 21C
D4BD	5'6", 9', 13', 25'	Lamp indicator, 14B, 17, 18 types
D4BR	2'6"	Subscriber set, 698A
D4BT	7', 14'	Loudspeaker set, 107A, subscriber set, 694-type
D6W	5'6", 9', 25'	Lamp indicator, 20B
D6AA	5'6", 9', 13'	Subscriber set, 698A-50
D6AD	5'6"	Auxiliary cord for 565HDR (MD) or 565LDR (MD) telephone set
D8P (MD)	5'6"	Plug, 274-type
D8S	7', 14'	Transmitter, 680A and 680C
D9H (MD)	1'9"	Mounting, KS-16705 (DRIVE-UP, WALK-UP)
D10R	5'6"	Auxiliary cord for 565HDR (MD) or 565LDR (MD) telephone set
D12E	15"	Mounting, telephone set, 751A, B and 2751A, B
D20H	5'6"	Key, 6040K
D20J (A&M Only)	8'	Subscriber set, 697A(MD)
D20N	7', 14'	Loudspeaker set, 108A
D26D*	7'	AE1 telephone base
D50G (MD)	8'	Subscriber set, 689B (MD)
D50H (MD)	5'6"	Subscriber set, 691A
D50N	5'6"	Key, 6040G
D50P (MD)	6'	Key, 6051
D50T	5'6"	Key, 6040J
D50AF	10'	2C video telephone station, PICTUREPHONE® visual telephone service
D120J (MD)	8'	Key, 6062A and B
KS-149884	6'	Power cord, loudspeaker set, 100F (MD)
M2CB (MD)	5'6"	Power cord, loudspeaker set, 100E (MD)
M2CC (MD)	5'6"	Mounting cord, loudspeaker set, 100E (MD)
M2FG	25'	Speakerphone, 4A
M5M	5'6"	Key, 549A and B
P-90D232	8"	Mounting, telephone sets, 750A, B and 2750A, B
R2DW	1'3", 3'6"	Mounting cord, loudspeaker set, 100F (MD)
R2FK	5'6"	Loudspeakers, 758A and 760A
T7A (MD)	5'6"	Transmitter, 666B

\* Used with 3A (Hospital) Communication System for Nurses' Call cord.