



Fig. 3 - 701B Telephone Set with E1A or E2A Ringer

TABLE B
LINE AND RINGER CONNECTIONS WITH E1A OR E2A RINGER

Wire or Lead	Individual or Bridged	Ring Party	Tip Party	Tip Party with Ident Grd		
				1000Ω	2650Ω	
Line at Ringer	Ring	R	5	5	6	6
	Tip	G	6	6	5	5
	Grd	Y	2	2	2	2
Ringer	R-R	7	7	7	7	1
	S-R	1	1	1	1	2
	BK	6	2	2	2	1
	S	1	1	1	1	7
Capacitor in Ringer	W	7	7	7	7	7
	Y	5	5	5	3	3
Transformer Leads at Ringer	1	2	2	2	2	2
	2	4	4	4	4	4
Mounting Cord at Ringer	R	5	5	5	5	5
	G	6	6	6	6	6
	Y	2	2	2	2	2
	BL	4	4	4	1	1
Mounting Cord at Set*	W	3	3	3	3	3
	BK	4	4	4	4	4
	R	L2	L2	L2	L2	L2
	G	L1	L1	L1	L1	L1
Mounting Cord at Set*	Y	3	3	3	3	3
	BL	4	4	4	B	B
	W	D	D	D	D	D
	BK	4	4	4	4	4

* Wired at factory for individual or bridged, ring- and tip-party service.