

Equipment Losses at 1000 Cycles

COMBINATIONS OF LINE EQUIPMENT FOR OPEN WIRE

(A) Side Circuit

93-A Coil ⁺	Type A or B Comp. Set	Any Type 3K or 5K Carrier Line Filter ⁺⁺	2-Wire 1000-Cycle Ringers*	Total
X				.7
X	X			1.0
X	X	X		1.3
X	X	X	X	1.5
X		X		1.0
X		X	X	1.2
X			X	0.9
X	X		X	1.2

(B) Phantom Circuit

93-A and 93-B Coils ⁺	Type A or B Comp. Set on Side	Any Type Carrier Line Filter on Side	2-Wire 1000-Cycle Ringers*	Total
X				.9
X	X			1.2
X	X	X		1.3
X	X	X	X	1.5
X		X		1.0
X		X	X	1.2
X			X	1.1
X	X		X	1.4

⁺ For 62-A or 62-B coil add 0.1.

⁺⁺ For 3K18 filter subtract 0.2.

* Except 30A2 and 31A2 types.